

Merlin Messaging Voice Mail Programming

Re-initialize a password in voice mail

1. Call into the voice mail by dialing extension 770 or pressing the “Get VM/Msgs” button on your phone
2. Enter 0# (the administrator’s mailbox)
3. Enter password of 123456#
4. Press 9 for programming
5. Press 2 for extensions
6. Enter extension number and #
7. Press 3 to re-initialize the mailbox password
8. Follow the prompts to save the changes (press *# to finish session)
9. Press **9 to exit programming.

Re-initialize a voice mail box (this will set the mailbox back to factory settings)

10. Call into the voice mail by dialing extension 770 or pressing the “Get VM/Msgs” button on your phone
11. Enter 0# (the administrator’s mailbox)
12. Enter password of 123456#
13. Press 9 for programming
14. Press 2 for extensions
15. Enter extension number and #
16. Press 4 to re-initialize the voicemail box
17. Follow the prompts to save the changes (press *# to finish session)
18. Press **9 to exit programming.

Merlin Messaging Voice Mail Programming

Change Mailbox Name and Directory Listing (“dial first four letters of person’s name”)

Call into the voice mail by dialing extension 770 or the “Get Msg.” Button

Enter 0# (the administrator’s mailbox #)

Enter password of 123456#

Press 9 for programming

Press 2 for extensions

Enter extension number and #

Press 1 to change the name (follow the prompts)

Press 2 for directory listing

Press 1 to change the directory listing

When prompted, enter the name:

To enter a “V”, press the 8 and the 3 to indicate the third letter on the 8 button

To enter a “C”, press the 2 and the 3 to indicate the third letter on the 2 button

Follow the prompts to finish.

Press *# to save your changes.

Press *# to back up in the menu tree.

Hang up when you are done.

Change # Rings before a call goes to voice mail from an extension:

From Console

Press the following:

Menu

System Programming

Exit

Extensions

Cover Delay

Group Cover

Enter Extension and press Enter

Enter desired number of rings and Enter

Home

Merlin Messaging Voice Mail Programming

Change Automated Attendant Greeting

Call into the voice mail (if you are calling in from outside the system press *7)

Dial administration mailbox number = 0#

Enter Password = 123456#

Press 9 for programming

Enter 3 for automated attendant

Enter automated attendant # (1 is usually the default)

Press 1 for Day or 2 for Night Menu

Press 2 to listen to the menu (press 1 to listen to the menu definition-this will play the greeting-after listening press *#)

Press 6 to modify the menu

Press *# to skip changing a selector code (a selector code is e.g. press 1 for sales or 2 for service etc.)

Press 1 to change the greeting

After recording- follow the prompts to listen to the new greeting or re-record the greeting

When prompted, press # to save all changes – important!